

KAPPA SERIES SAVING, LOADING, AND LABELING WIRES

- 1) From any screen press function key that corresponds to the "List" function, or press the button labeled "Main" and then press "F3"
- 2) Enter a number between 1 and 150, then press the "Enter" button. If there is already a wire at the number you choose and you do not want to lose that wire data, select a different number and again press the "Enter" button.
- 3) Press "6" to save the wire data. If the wire number you choose is larger than the value entered for write protection in the "CONF" menu, the data is not saved and a signal sounds.

KAPPA SERIES SAVING, LOADING, AND LABELING WIRES

Labeling a Saved Wire

1) From the wire list, select the wire number you wish to label and press the "Enter" button.

2) Press "F4"

3) Use the arrow keys to select a letter and push "Enter" to accept a selected letter.

To select a number, use the number key pad. Use the "bs" button to delete a character. To change the cursor position, use the "-" and "+" buttons.

4) The input is completed by pressing the "F4" button.

KAPPA SERIES SAVING, LOADING, AND LABELING WIRES

Loading a Wire

- 1) From any screen press the "F" button that is under the word "LIST" or press the button labeled "MAIN" and then press "F3".
- 2) Enter a number between 1 and 150, then press the "ENTER" button.
- 3) Press "F5" to load the wire data.